



### Features:

- Adjustable threshold.
- Din rail mounted
- 10 years of reliable history
- Off the shelf

## Application

The Lamp Proving Module is used to monitor the current flowing in a 120Vac lamp circuit. It provides an output which is OFF when the current is below a pre-set threshold level for more than 0.25 seconds.

The pre-set threshold is adjustable for a current in a measured circuit between 50mA and 250mA RMS.

## Technical Data

Description	
Mounting	DIN Rail NS32 or NS35/7.5
Termination	Screw connection – see below
Power supply range	40-70V DC
Threshold Current Adjust	50-250mA RMS

Connections	
Terminal 1	Positive Supply 50V (nominal)
Terminal 2	Negative Supply 50V (nominal)
Terminal 3	Chassis
Terminal 4	Chassis
Terminal 5	Switched Positive Output (50V nominal)
Terminal 6	Switched Negative Output

## Part Number

The part number is XP3510 – 1000

**e:** sales@ar-tech.com.au

**p:** +61 2 9482 5710

**w:** ar-tech.com.au